



FET-100 Gigabit Ethernet Tester

- Electrical port and optical ports with rate at 10/100/1000Mbps
- Smart and durable, field application ready
- 5 inch LCD color touch screen, smart navigation menu
- Results can be shown graphically and numerically
- RFC2544 auto test, quickly find the fault
- Full Y.1564 test
- LED indicator light, on-screen display and ICON
- Large capacity memory to save settings and test results
- Embedded software to easy upgrade

Items	Specifications
Testing Port	Dual-RJ45 port:10/100/1000 BASE-T Dual-SFP port: 1000BASE-SX/LX/ZX
Standard	IEEE 802.3 ,RFC1242,RFC2544,Y.1564
Connector	RJ-45/USB
LED Indicator	POWER,PORT1LINK/ACT,PORT2 LINK/ACT ,ALARM 800×480 color LCD touch screen
Display	800×480 color LCD touch screen
Battery	Lithium battery / AC adapter
Working Time	4 hours continuous operation
Operating Temperature	0°C~50°C
Relative Humidity	0 to 95% (non-condensing)
Weight	800g
Dimension	233×110×64mm